

20 CHANNELS NTC SIMULATOR NTC-20-1-7M



OVERVIEW

The 20 Channels NTC Simulator is used to simulate NTC resistors temperature sensing features. This board contains 4 isolated channels that can be controlled or adjusted by software via CAN. A single board can be used or several in series according to the The current for each channel can be measured with the software.

DIMENSION

L*W*H =
602mm*482.6mm*88.1mm

KEY FEATURES

- 20 independent channels in total.
- Extendable number of channels by adding more boards
- Each channel has adjusted resistance value from 0 Ω to 8.1 M Ω at a resolution of 1 Ω .
- Controllable by USB,TCP/IP.

OPERATING TEMPERATURE

-20 °C ~ +60 °C

POWER REQUIREMENT

DC Power Supply:
24 VDC, 1 A

Working Voltage Range:
9 V – 36 V (Default 24 V)

USAGE EXAMPLES

Mainly used to simulate NTC temperature sensors. For example: If you need to test your BMS (battery management system), the NTC simulator board offers a software configurable ready to use solution.

NTC DETAILED SPECIFICATIONS:

Resistance	Value	Unit
Range	0 to 8.1 M	Ω
Resolution	1	Ω

The 20 Channels NTC Simulator is intended for indoor use only but may be used outdoors if installed in a suitable enclosure. Refer to the manual for more information about meeting these specifications.

Operating temperature

-40 °C -- +55 °C

Storage temperature

-40 °C -- +85 °C

Ingress protection (IP code)

None

Operating humidity

10-90% RH non condensing

Storage humidity

5-95% RH non condensing

SUPPORT AND SERVICES

Calibration

ART logics measurement hardware is calibrated to ensure measurement accuracy and verify that the device meets its published specifications. To ensure the ongoing accuracy of the measurement hardware, ART logics offers basic or detailed recalibration service.



ART Logics (Shanghai) Testing Equipment CO., Ltd
艾驰电子检测设备技术（上海）有限公司

Tel: 021-61075469
Room 105, No. 258, Chengjiaqiao Road, Shanghai, P.R. China



www.art-logics.com
support@art-logics.com